

SECUREX CONNECT PRO

SecureX HeatSense –
värmedetektor med
10-årsbatteri (BS5446-
2)

SSHEAT-050-SX

v1.0

Datum: 2026-02-16



PRODUCT DATASHEET / MANUAL

Product Name	SecureX HeatSense – Heat Detector with 10-Year Battery (BS5446-2)
SKU / Article Number	SSHEAT-050-SX
Version	v1.0
Date	2026-02-16
Document Type	Datasheet + Manual

Short Summary

SecureX HeatSense is a certified heat detector according to BS5446-2 that detects abnormal temperature increases that may indicate fire. It is particularly suitable for areas where smoke detectors may cause false alarms, such as kitchens, garages, workshops, and dusty environments.

In case of dangerous temperature rise, a siren of ≥ 85 dB (at 3 meters) is activated along with a clear LED indicator. The built-in battery has a lifespan of up to 10 years, ensuring minimal maintenance.

SECUREX CONNECT PRO

SecureX HeatSense – SSHEAT-050-SX

v1.0

Datum: 2026-02-16

värmedetektor med
10-årsbatteri (BS5446-
2)

DATASHEET

1. Key Features

- Certified according to BS5446-2
- 10-year battery (replaceable) for long lifespan
- Powerful siren ≥ 85 dB (at 3 meters) with LED indication
- Interconnected fire protection: all smoke and heat detectors alarm simultaneously (via SecureX hub)
- Real-time notifications in the Stonehouse Smart app
- Wireless frequency: 433 MHz (EV1527), coded for SecureX
- Supports connection of up to 40 smoke and heat detectors
- Range up to 100 m (open space)
- Simple and discreet ceiling installation

2. Technical Specifications

Modell / Artikelnr	SSHEAT-050-SX
Certification	BS5446-2
Siren	≥ 85 dB (vid 3 meter)
Indication	LED
Battery	10-årsbatteri (utbytbart)
Communication	433 MHz (EV1527) + SecureX-kodning
Range	Upp till 100 m (fri sikt)
Max units in network	Upp till 40 rök- och värmedetektorer (via hubben)
App	Stonehouse Smart (iOS/Android)
Compatibility	Tuya & Smart Life via SecureX-hubben
Size	116 x 46 mm (rund)
Weight	88 g

3. Package Contents

- 1x SecureX HeatSense värmedetektor
- 2x Skruvar
- 2x Plugg
- 1x Manual

SECUREX CONNECT PRO

SecureX HeatSense – SSHEAT-050-SX
värmedetektor med
10-årsbatteri (BS5446-
2)

v1.0

Datum: 2026-02-16

MANUAL

4. Interconnected Fire Protection

HeatSense är en del av SecureX brandsystem och används tillsammans med SecureX-hubben. När en rök- eller värmedetektor i systemet löser ut larmar alla enheter samtidigt, sirener aktiveras i hela fastigheten och pushnotiser skickas i realtid. Larmet stängs av via SecureX-hubben eller i Stonehouse Smart-appen.

5. Installation

1. Montera enheten i taket enligt medföljande anvisningar.
2. Öppna Stonehouse Smart-appen och lägg till enheten via SecureX-hubben (parningsläge enligt hubbens instruktioner).
3. Verifiera att enheten visas i appen och genomför ett funktionstest enligt anvisningarna.

6. App Control & Compatibility

Alla händelser visas i Stonehouse Smart-appen. HeatSense kopplas till SecureX-hubben. Compatibility med Tuya och Smart Life sker via hubben (enheten är inte kompatibel direkt utan hubb).

7. Troubleshooting

Problem	Åtgärd
No notification during alarm	Check that the hub has internet connection and that push notifications are enabled in the app.
Unable to add device	Ensure the hub is in pairing mode and keep the device close to the hub during first pairing.
Short range	Place the sensor closer to the hub and avoid obstacles/metal between the units, or purchase SecureX SignalMax.

Category: SecureX Connect Pro